

# Motorola Semiconductor Engineering Bulletin

---

## EB265

### Generating Edge-Sensitive Interrupts on the MC683xx and MC68HC16 Families of MCUs

By Charles Melear  
Austin, Texas

#### General Information

---

One method for generating edge-sensitive interrupts (interrupts that are recognized only when the pin state changes) is to use an input to a peripheral module such as the general-purpose timer or the time processor unit.

For the general-purpose timer (GPT), an input capture pin or pulse accumulator input pin can be used. The pin should be set up to recognize an edge of a particular polarity, for instance, positive only or negative only. Of course, interrupts must be enabled for the GPT and the GPT's IARB field set to a non-zero value. When the edge occurs, a flag in the GPT's registers will be set and an interrupt will be signaled. The flag does not go away until the processor takes a specific action, such as reading the flag as a 1 and then clearing it by writing the flag to a 0.

A similar method can be used on the time processor unit (TPU). A channel can be set up in the DIO mode and programmed to recognize the desired edge. Once again, a flag will be set and an interrupt signaled. The flag must be cleared by a specific action of the CPU.



In either case, the flag and associated interrupt remains asserted regardless of whether the actual interrupt signal remains asserted or not. Also, a second interrupt is not created until the incoming signal first goes to its de-asserted state and then is asserted a second time.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

#### How to reach us:

**USA/EUROPE/Locations Not Listed:** Motorola Literature Distribution, P.O. Box 5405, Denver, Colorado 80217, 1-800-441-2447 or 1-303-675-2140. Customer Focus Center, 1-800-521-6274

**JAPAN:** Nippon Motorola Ltd.: SPD, Strategic Planning Office, 141, 4-32-1 Nishi-Gotanda, Shinagawa-ku, Tokyo, Japan. 03-5487-8488

**ASIA/PACIFIC:** Motorola Semiconductors H.K. Ltd., 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

**Mfax™, Motorola Fax Back System:** RMFAX0@email.sps.mot.com; <http://sps.motorola.com/mfax/>;

TOUCHTONE, 1-602-244-6609; US and Canada ONLY, 1-800-774-1848

**HOME PAGE:** <http://motorola.com/sps/>

Mfax is a trademark of Motorola, Inc.



**MOTOROLA**

© Motorola, Inc., 1998

EB265/D